



HDBase T HDMI Over Cat5e Wall Plate

1.0 Disclaimer

The purchase and usage of Belkin HDBase T HDMI Over Cat5e Wall Plate is for indoor application only. Belkin HDBase T HDMI Over Cat5e Wall Plate should only be installed by a licensed electrician skilled in the field of low voltage indoor cable installs. The Belkin HDBase T HDMI over Cat5e solution is not intended for do-it-yourself installation as critical damage to building, hardware and bodily harm may occur if not properly installed. This HDBaseT unit will operate at a high temperature which is normal and will not disturb performance. Belkin recommends to allow for proper air flow during installation and avoid physical contact with other devices once product is installed.

2.0 Product Description

Belkin HDBase T HDMI Over Cat5e Wall Plate are AV distribution over Cat5e cabling connecting AV sources to projectors, displays, and TVs over Cat5e cable.

Belkin HDBase T HDMI over Cat5e Wall Plate:

- 1 to 1 HDMI over Cat5e Wall Plate: 100M.

3.0 Installation

IMPORTANT: The graphic card capability must match the monitor resolution in order to get the maximum resolution performance. Belkin HDBase T HDMI over Cat5e Wall Plate will only perform up to the best graphical output and monitor display capability.

1. Belkin components required
 - a. HDBase T HDMI over Cat5e Wall Plate set: TX & RX wall plates and respective power adapters.
 - b. Belkin brand Cat5e cable or equivalent
 - c. Belkin-brand HDMI Cable or equivalent
2. Tools required
 - a. Phillips screwdriver if the included mount plate is used
3. Initial Setup
 - a. Identify the Transmitter and Receiver units
 - i. Transmitter (labeled on the front panel) is the input source side: DVD, PC, or Media player
 - ii. Receiver (labeled on the front panel) is the output display side: Projector, monitor, or TV
 - b. Verify that the Cat5e cable length matches the transmitter & receiver distance limitation
 - c. Verify that 110VAC is available within 3 feet for power adapters
4. Installation:
 - a. With electrical junction box and conduit
 - i. Install electrical conduit and junction boxes at the TX & RX locations according to local electrical codes.
 - ii. Pull Cat5e cable through conduit using pull rod, fish tape, or pull line attached to pull cap.
 - iii. Remove pull caps and connect ends of Cat5e cable to HDBase T HDMI Wall Plates.
 - iv. Connect power adapters to HDBase T HDMI Wall Plates.
 - v. Attach HDBase T HDMI Wall Plates to junction box.
 - b. Without electrical junction box and conduit
 - i. Drill the mounting holes according to the front panel hole and the insert wall anchor screws.
 - ii. Pull Cat5e cable from one wall-plate hole to the other using pull rod, fish tape, or pull line attached to pull cap.
 - iii. Remove pull cap and connect Cat5e Cable to HDBase T HDMI Wall Plates.
 - iv. Connect power adapters to HDBase T HDMI Wall Plates.
 - v. Attach HDBase T HDMI Wall Plate to the anchored holes on the wall.
5. Connect source and display to the respective wall plates. We recommend Belkin-brand, HDMI Cables.

4.0 HDMI Wall Plate Instructions

Belkin HDBase T HDMI over Cat5e transmitter and receiver wall plate are labeled on the individual front panel:

- Verify HDMI monitor & player equipment share compatible graphic output type and resolution.

- HDBase T HDMI Wall Plate will not upscale video to 1080p if the source is not rated 1080p.
- Once the Cat5e cable is connected to the transmitter and receiver wall plate, plug in the power adapter before turning on the monitor and player.
- HDBase T HDMI transmitter & receiver wall plate are plug & play, no additional adjustments needed.

5.0 Troubleshooting

Problem: I am getting ghosting, shadowing, or fuzzy images on my monitor.

Solution:

- Check that all video cables are inserted properly.
- Check that the monitor supports the resolution and refresh rate setting on your computer.
- Check that the graphic card supports the resolution and refresh rate setting on your computer.
- Hit auto adjust on monitor to see if the problem still appears.
- Check that the Cat5e cable is properly installed and correct length for the transmitter & receiver wall plate.

Problem: I am getting ghosting, shadowing, or fuzzy images on my TV.

Solution:

- Check that all video cables are inserted properly.
- Check that the TV supports the resolution and refresh rate setting on your DVD player.
- Check that the DVD player supports the resolution and refresh rate setting on your TV.
- Hit auto adjust on TV to see if the problem still appears.
- Check that the Cat5e cable is properly installed and correct length for the transmitter & receiver wall plates.

Problem: I am getting a black screen.

Solution:

- Check that all video cables are inserted properly.
- If a power adapter is used, check that the power adapter is properly connected.
- Connect the computer or DVD player directly to the monitor or TV to see if the problem persists.
- Hit auto adjust on monitor to see if the problem still appears.
- Check that the Cat5e cable is properly installed and correct length for the transmitter & receiver wall plate.

6.0 Warranty

Belkin International, Inc., Limited 3-Year Product Warranty

Belkin International, Inc. ("Belkin") warrants to the original purchaser of this Belkin product that the product shall be free of defects in design, assembly, material, or workmanship.

What will we do to correct problems?

Product warranty: Belkin will repair or replace, at its option, any defective product free of charge (except for shipping charges for the product). Belkin reserves the right to discontinue any of its products without notice, and disclaims any limited warranty to repair or replace any such discontinued products. In the event that Belkin is unable to repair or replace the product (for example, because it has been discontinued), Belkin will offer either a refund or a credit toward the purchase of another product from Belkin.com in an amount equal to the purchase price of the product as evidenced on the original purchase receipt as discounted by its natural use.

What is not covered by this warranty?

All above warranties are null and void if the Belkin product is not provided to Belkin for inspection upon Belkin's request at the sole expense of the purchaser, or if Belkin determines that the Belkin product has been improperly installed, altered in any way, or tampered with. The Belkin Product Warranty does not protect against acts of God such as flood, lightning, earthquake, war, vandalism, theft, normal-use wear and tear, erosion, depletion, obsolescence, abuse, damage due to low voltage disturbances (i.e. brownouts or sags), non-authorized program, or system equipment modification or alteration.

How to get service.

To get service for your Belkin product you must take the following steps:

1. Contact Belkin International, Inc. at 12045 E. Waterfront Drive Playa Vista, CA 90094, Attn: Customer Service, or call (800)-223-5546, within 15 days of the Occurrence. Be prepared to provide the following information:

- a. The part number of the Belkin product.
- b. Where you purchased the product.
- c. When you purchased the product.
- d. Copy of original receipt.

2. Your Belkin Customer Service Representative will then instruct you on how to forward your receipt and Belkin product and how to proceed with your claim. Belkin reserves the right to review the damaged Belkin product. All costs of shipping the Belkin product to Belkin for inspection shall be borne solely by the purchaser. If Belkin determines, in its sole discretion, that it is impractical to ship the damaged equipment to Belkin, Belkin may designate, in its sole discretion, an equipment repair facility to inspect and estimate the cost to repair such equipment. The cost, if any, of shipping the equipment to and from such repair facility and of such estimate shall be borne solely by the purchaser. Damaged equipment must remain available for inspection until the claim is finalized. Whenever claims are settled, Belkin reserves the right to be subrogated under any existing insurance policies the purchaser may have.

How state law relates to the warranty.

THIS WARRANTY CONTAINS THE SOLE WARRANTY OF BELKIN. THERE ARE NO OTHER WARRANTIES, EXPRESSED OR, EXCEPT AS REQUIRED BY LAW, IMPLIED, INCLUDING THE IMPLIED WARRANTY OR CONDITION OF QUALITY, MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE, AND SUCH IMPLIED WARRANTIES, IF ANY, ARE LIMITED IN DURATION TO THE TERM OF THIS WARRANTY.

Some states do not allow limitations on how long an implied warranty lasts, so the above limitations may not apply to you.

IN NO EVENT SHALL BELKIN BE LIABLE FOR INCIDENTAL, SPECIAL, DIRECT, INDIRECT, CONSEQUENTIAL OR MULTIPLE DAMAGES SUCH AS, BUT NOT LIMITED TO, LOST BUSINESS OR PROFITS ARISING OUT OF THE SALE OR USE OF ANY BELKIN PRODUCT, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

This warranty gives you specific legal rights, and you may also have other rights, which may vary from state to state. Some states do not allow the exclusion or limitation of incidental, consequential, or other damages, so the above limitations may not apply to you.

7.0 Tech Support

Belkin Tech Support

US: 800-223-5546 ext. 2263
310-898-1100 ext. 2263

UK: 0845 607 77 87

Australia: 1800 235 546

New Zealand: 0800 235 546

Singapore: 65 64857620

Belkin International, Inc.

12045 E. Waterfront Drive
Playa Vista, CA 90094, USA
310-751-5100
310-898-1111 fax

Belkin Ltd.

Europe: www.belkin.com/support

Belkin Ltd.

4 Pioneer Avenue
Tuggerah Business Park
Tuggerah, NSW 2259, Australia
+61 (0) 2 4350 4600
+61 (0) 2 4350 4700 fax

Express Business Park, Shipton Way
Rushden, NN10 6GL, United Kingdom
+44 (0) 1933 35 2000
+44 (0) 1933 31 2000 fax

Belkin B.V.

Tupolevlaan 1
1119 NW Schiphol-Rijk, The Netherlands
+31 (0) 20 711 8000
+31 (0) 20 654 7349 fax

© 2012 Belkin International, Inc. All rights reserved. All trade names are registered trademarks of respective manufacturers listed.